

Cudy X6 AX1800 Dual Band 2.4+5Ghz MESH Wi-Fi Ruter 1W/4LAN Gbit, 4x5dBi Wisp/AP/REP/VPN/TR069

Šifra: 29440

Kategorija proizvoda: Mrežna oprema

Proizvođač: CUDY

Cena: 5.050,00



- Dual-Band Wi-Fi 6 Up to 1.8 Gbps
- Up to 1201Mbps Wi-Fi Speed on 5GHz
- Up to 574Mbps Wi-Fi Speed on 2.4GHz
- Dual-Core CPU ensures high-speed network operation
- Gigabit ports provide fast, stable connections
- High gain antennas provide excellent signal strength
- VPN clients help establish secure connections
- Dynamic DNS facilitates the router's remote management
- Support WPA3 Security

Processor: Dual-Core CPU

Flash: 16MB

DDR: 256MB

Antenna: 4 × Fixed Omni-Directional Antennas

Interface:

-1 × 1000/100/10 Mbps WAN Port

-4 × 1000/100/10 Mbps LAN Ports

Button: WPS Button, Reset Button

External Power Supply: 12 V/1 A

Dimensions (W x D x H) 204.8 x 137. 5 x 38. 3mm

Wireless Standards:

IEEE 802.11ax/ac/n/a 5 GHz

IEEE 802.11ax/n/b/g 2.4 GHz

Frequency: 5 GHz, 2.4 GHz

Signal Rate:

1201Mbps (5GHz), 574Mbps (2.4GHz)

Compatible with 802.11a/b/g/n/ac Wi-Fi standards

Transmit Power

CE: FCC: Wireless Modes Enable/Disable Wireless Radio, WMM

Wireless Security WEP, WPA/WPA2, WPA-PSK/WPA2-PSK,WPA3

Software Features:

WAN Type: Dynamic IP/Static IP/PPPoE

Management: Parental Control

Guest Network

DHCP: Server, DHCP Client List, Address Reservation

Dynamic DNS Compatible with 15 more DDNS providers

Guest Network 2.4GHz guest network × 1

5GHz guest network × 1

NAT: Port Forwarding, Port Triggering, UPnP, DMZ

VPN Client: PPTP/L2TP/OpenVPN/WireGuard/IPSec/Zerotier

Package Contents:

AX1800 Wi-Fi 6 Router

Power Adapter

RJ45 Ethernet Cable

Quick Installation Guide

System Requirements:

Microsoft Windows 98SE/NT/2000/XP/Vista™/7/8/8.1/10, MAC OS,

NetWare, UNIX or Linux

Internet Explorer 11, Firefox 12.0, Chrome 20.0, Safari 4.0, or other Java-enabled browser

Cable or DSL Modem

Subscription with an internet service provider (for internet access)